



240.1696RV

CLAVIJA MURAL

16A 3P+T 6h 380-415V 50Hz 60Hz Bornes con tornillo Con el dispositivo REVERSE

Product Approvals

| TECHDATA | | STANDARDS AND LAWS | |
|------------------------------|----------------------|-----------------------------------|---|
| Tipo de producto | CLAVIJA MURAL | EN 60309-1 (1999) | [European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements |
| Serie comercial | Serie OPTIMA-REVERSE | EN 60309-2 (1999) | [European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 2: Dimensional interchangeability requirements for pin and contact-tube accessories of harmonized configurations |
| Descripción | CLAVIJA MURAL | EN 60309-1/A1 (2007) | [European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements |
| Tipo de instalación | MURAL | EN 60309-2/A1 (2007) | [European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 2: Dimensional interchangeability requirements for pin and contact-tube accessories of harmonized configurations |
| Intensidad nominal | 16A | EN 60309-1/A2 (2012) | [European Standard] Plugs, socket-outlets and couplers for industrial purposes. Part 1: General requirements |
| Polos | 3P+T | DIRECTIVE LOW VOLTAGE 2014/35 /UE | [European Directives] Low Voltage Directive |
| Posición de hora | 6h | | |
| Tensión nominal (range) | 250-400V | | |
| Tensión nominal | 380-415V | | |
| Frecuencia nominal | 50Hz | | |
| Frecuencia nominal | 60Hz | | |
| Color | ROJO | | |
| Material | TERMOPLÁSTICO | | |
| Grado de protección | Splash proof | | |
| Grado de protección IP | IP44/IP54 | | |
| Grado de protección IK | IK08 | | |
| Tipos de salidas disponibles | INCLINADA | | |
| Bornes | Bornes con tornillo | | |

| | |
|-------------------------------|-----------------------------|
| Material de los contactos | CuZn (latón) |
| Tratamiento superficial cont. | Con revestimiento de níquel |
| Salida del cable | M25X1,5 |
| Opciones | Con el dispositivo REVERSE |